

Evolution Not Revolution

The Just Add Power 2GΩ/3G+ Transmitter combines the enhanced audio and feature-set of the 3G system with the **maximum 1080p resolution** of 2G devices.

2GΩ/3G+ devices can be installed in 2G and 3G systems.

In 2G systems, a 2GΩ/3G+ Transmitter is a direct replacement to a 2G+ Transmitter and functions just like a 2G+ device.

In 3G systems, 2GΩ/3G+ Transmitters provide a lower-cost solution for sources that output **1080p resolution or lower**.

Build a future-proof infrastructure. Just Add Power 2GΩ/3G+ integrates seamlessly with both 2G and 3G. Build a 2GΩ system with 4K expansion plans or mix-and-match with 2GΩ on 1080p sources and 3G on 4K sources!



Compliance	HDCP 1.4 & RoHS/FCC/CE
Supported Video & Audio	Up to 1920x1200 Uncompressed multi-channel audio
Encryption	Hardware-Based AES 256-bit Encryption of Network Video Signal
Ports	Gigabit Ethernet HDMI In & HDMI Out 3.5mm Stereo Out 3.5mm RS232 w/ null modem Micro-USB
Dimensions & Weight	158x30x127mm/6.2x1.2x5.0 inch 0.36 kg / 0.8 lb
Operating Temp	0-60 °C / 32-140 °F
Bandwidth	180-500 Mbps
Power Supply (not included)	~4.7 – 23V 5.5mm/2.1mm, Positive tip
PoE	10 watts maximum

Features
Maximum 1080p video with HDCP 1.4
All lossless audio supported – including Dolby Atmos®
Control endpoints with RS232 & IR*
Image Play – Push, Pull & Pop
Integrated Scaler on Receiver
CEC control
HDMI pass-through
Stereo audio output with 170ms audio delay*
USB 2.0



HDMI IN

HDMI OUT

STEREO

RS232

USB

All measurements in millimeters (mm)

