



Just Add  
Power

767DSS  
3G+ Dante® Sound System Transmitter

ULTRA<sup>HD</sup>

## Dante® Compatibility

The Just Add Power 3G+ Dante® Sound System Transmitter adds compatibility with Dante® and AES67 audio networks to the UltraHD over IP system.

**Input up to 8 channels** into the Dante® network.

**Extract up to 8 channels** from the Dante® network, embed onto the HD over IP signal, and distribute across the Just Add Power network.

**Mix-and-match!** The 3G+ Dante® Sound System Transmitter is fully compatible with all 2GΩ/3G and 3G devices.

**Not just for Dante®.** AES67 compatibility for interoperability with other leading audio-over-IP technologies



## Features

Ultra HD & 4K video with HDCP 2.2

Dante® Broadway Chip Set

Send and receive up to 8 channels

Inject audio into the J+P network

AES67 compatibility mode

HDMI pass-through

Control endpoints with RS232 & IR\*

Compliance	HDCP 2.2 & RoHS/FCC/CE
Operating Temp	0-60 °C / 32-140°F
Supported Resolutions	Up to 4096x2160 (interlaced & progressive)
Dimensions & Weight	184 x 30 x 152 mm 7.2" x 1.2" x 6.0" 0.54kg / 1.2lb
Ports	J+P Gigabit Ethernet HDMI In HDMI Out 3.5mm RS323 w/ null modem Dante® Gigabit Ethernet
Bandwidth	180-850 Mbps
Power Supply (not included)	~4.7 – 23V 5.5 mm/2.1mm, Positive tip
PoE	10 watts maximum

